

STROJNI UKAZI PROCESORJA Z80 IN NJIHOVI KODI

ADC A, (HL)	BE	ADD IV, IV	FD 29
ADD A, (IX+dis)	DD BE XX	ADD IV, SP	FD 39
ADC A, (IY+dis)	FD BE XX	AND A, (HL)	A6
ADC A, A	BF	AND A, (IX+dis)	DD A6 XX
ADC A, B	88	AND A, (IY+dis)	FD A6 XX
ADC A, C	89	AND A, A	A7
ADC A, D	8A	AND A, B	A0
ADC A, E	8B	AND A, C	A1
ADC A, H	8C	AND A, D	A2
ADC A, L	8D	AND A, E	A3
ADC A, n	CE XX	AND A, H	A4
ADC HL, BC	ED 4A	AND A, L	A5
ADC HL, DE	ED 5A	AND A, n	E6 XX
ADC HL, HL	ED 6A	BIT 0, (HL)	CB 46
ADC HL, SP	ED 7A	BIT 0, (IX+dis)	DD CB XX 46
ADD A, (HL)	86	BIT 0, (IY+dis)	FD CB XX 46
ADD A, (IX+dis)	DD 86 XX	BIT 0, A	CB 47
ADD A, (IY+dis)	FD 86 XX	BIT 0, B	CB 40
ADD A, A	87	BIT 0, C	CB 41
ADD A, B	80	BIT 0, D	CB 42
ADD A, C	81	BIT 0, E	CB 43
ADD A, D	82	BIT 0, H	CB 44
ADD A, E	83	BIT 0, L	CB 45
ADD A, H	84	BIT 1, (HL)	CB 4E
ADD A, L	85	BIT 1, (IX+dis)	DD CB XX 4E
ADD A, n	C6 XX	BIT 1, (IY+dis)	FD CB XX 4E
ADD HL, BC	09	BIT 1, A	CB 4F
ADD HL, DE	19	BIT 1, B	CB 48
ADD HL, HL	29	BIT 1, C	CB 49
ADD HL, SP	39	BIT 1, D	CB 4A
ADD IX, BC	DD 09	BIT 1, E	CB 4B
ADD IX, DE	DD 19	BIT 1, H	CB 4C
ADD IX, IX	DD 29	BIT 1, L	CB 4D
ADD IX, SP	DD 39	BIT 2, (HL)	CB 56
ADD IY, BC	FD 09	BIT 2, (IX+dis)	DD CB XX 56
ADD IY, DE	FD 19	BIT 2, (IY+dis)	FD CB XX 56