

STROJNI KODI PROCESORJA Z80 IN NJIHOVI UKAZI

00	NOP	24	INC H	4B	LD C, B	71	LD (HL), C
01	XX XX	LD BC, nn	25	DEC H	49	LD C, C	72
02		LD (BC), A	26	LD H, n	4A	LD C, D	72
03		INC BC	27	DAA	4B	LD C, E	73
04		INC B	28	JR Z, dis	4C	LD C, H	74
05		DEC B	29	ADD HL, HL	4D	LD C, L	75
06	XX	LD B, n	2A	XX XX	4E	LD C, (HL)	HALT
07		RLCA	2B	LD HL, (naslov)	4F	LD C, A	LD (HL), A
08		EX AF, A'F'	2C	DEC HL	50	LD D, B	LD A, B
09		ADD HL, BC	2D	INC L	51	LD D, C	LD A, D
0A		LD A, (BC)	2E	DEC L	52	LD D, D	LD A, E
0B		DEC BC	2F	LD L, n	53	LD D, E	LD A, H
0C		INC C	30	DEC HL	54	LD D, H	LD A, L
0D		DEC C	31	XX XX	55	LD D, L	LD A, (HL)
0E	XX	LD C, n	32	LD SP, nn	56	LD D, (HL)	LD A, A
0F		RRCA	33	LD (naslov), A	57	LD D, A	ADD A, B
10	XX	DJNZ dis	34	INC SP	58	LD D, B	ADD A, C
11	XX XX	LD DE, nn	35	INC (HL)	59	LD E, C	ADD A, D
12		LD (DE), A	36	DEC (HL)	60	LD E, D	ADD A, E
13		INC DE	37	LD (HL), n	61	LD E, E	ADD A, H
14		INC D	38	SCF	62	LD E, H	ADD A, L
15		DEC D	39	JR C, dis	63	LD E, L	ADD A, (HL)
16	XX	LD D, n	40	ADD HL, SP	64	LD E, (HL)	ADD A, A
17		RLA	3B	LD A, (naslov)	65	LD E, A	ADC A, B
18	XX	JR dis	3C	DEC SP	66	LD E, B	ADC A, C
19		ADD HL, DE	3D	INC A	67	LD H, B	ADC A, H
1A		LD A, (DE)	3E	DEC A	68	LD H, C	ADC A, D
1B		DEC DE	3F	LD A, n	69	LD H, D	ADC A, E
1C		INC E	40	CCF	70	LD H, E	ADC A, H
1D		DEC E	41	LD B, B	71	LD H, F	ADC A, L
1E	XX	LD E, n	42	LD B, C	72	LD H, (HL)	ADC A, (HL)
1F		RRA	43	LD B, B	73	LD H, L	ADC A, A
20	XX	JR NZ, dis	44	DEC A	74	LD H, (HL)	SUB D
21	XX XX	LD HL, nn	45	LD A, n	75	LD H, A	SUB B
22	XX XX	LD (naslov), HL	46	CCF	76	LD H, B	SUB C
23		INC HL	47	LD B, (HL)	77	LD H, C	SUB E
				LD B, A	78	LD H, L	SUB H
				LD (HL), B	79	SUB L	SUB (HL)