

D.6. 80-COLUMN CARD CODE, SYMBOL, XS-3, FIELDATA, EBCDIC, BCD CONVERSION TABLE

Table D-6 cross references printer symbols with the card punch, XS-3, Fieldata, EBCDIC, and BCD codes.

80-Column Card Code	High-Speed Printer Symbol	XS-3		Fieldata		EBCDIC		BCD	
		Octal	Octal	Octal	Octal	Hexadecimal	Octal	Octal	
12-1	A	24	06	C1	61				
12-2	B	25	07	C2	62				
12-3	C	26	10	C3	63				
12-4	D	27	11	C4	64				
12-5	E	30	12	C5	65				
12-6	F	31	13	C6	66				
12-7	G	32	14	C7	67				
12-8	H	33	15	C8	70				
12-9	I	34	16	C9	71				
11-1	J	44	17	D1	41				
11-2	K	45	20	D2	42				
11-3	L	46	21	D3	43				
11-4	M	47	22	D4	44				
11-5	N	50	23	D5	45				
11-6	O	51	24	D6	46				
11-7	P	52	25	D7	47				
11-8	Q	53	26	D8	50				
11-9	R	54	27	D9	51				
0-2	S	65	30	E2	22				
0-3	T	66	31	E3	23				
0-4	U	67	32	E4	24				
0-5	V	70	33	E5	25				
0-6	W	71	34	E6	26				
0-7	X	72	35	E7	27				
0-8	Y	73	36	E8	30				
0-9	Z	74	37	E9	31				
0	0	03	60	F0	12				
1	1	04	61	F1	01				

Table D-6. 80-Column Card Code, Symbol, XS-3, Fieldata, EBCDIC, BCD Conversion Table (Part 1 of 3)

80-Column Card Code	High-Speed Printer Symbol	XS-3		Fieldata		EBCDIC		BCD	
		Octal	Octal	Octal	Octal	Hexadecimal	Octal	Octal	
2	2	05	62	F2	02				
3	3	06	63	F3	03				
4	4	07	64	F4	04				
5	5	10	65	F5	05				
6	6	11	66	F6	06				
7	7	12	67	F7	07				
8	8	13	70	F8	10				
9	9	14	71	F9	11				
12	+	20	42	50	60				
11	-(minus)	02	41	60	40				
12-0	?	23	54	6F	72				
11-0	/	43	55	5A	52				
0-1	/	64	74	61	21				
2-8	&	63	46	7A	00 or 60*				
3-8	=	35	44	78	13				
4-8	' (apos)	56	72	7C	14				
5-8	:	21	53	7D	15				
6-8	>	76	45	7E	16				
7-8	@	40	00	7F	17				
12-3-8	.	22	75	48	73				
12-4-8	)	75	40	4C	74				
12-5-8		17	01	4D	75				
12-6-8	<	36	43	4E	76				
12-7-8	#	37	03	4F	77				
11-3-8	\$	42	47	58	53				
11-4-8	.	41	50	5C	54				
11-5-8		01	02	5D	55				
11-6-8	/	16	73	5E	56				
11-7-8	Δ	57	04	5F	57				
0-2-8	≠	60	77	EO	32				
0-3-8	.(comma)	62	56	68	33				

Table D-6. 80-Column Card Code, Symbol, XS-3, Fieldata, EBCDIC, BCD Conversion Table (Part 2 of 3)