

SBC HL, SP	ED 72	SET 3, L	CB DD
SCF	37	SET 4, (HL)	CB E6
SET 0, (HL)	CB C6	SET 4, (IX+dis)	DD CB XX E6
SET 0, (IX+dis)	DD CB XX C6	SET 4, (IV+dis)	FD CB XX E6
SET 0, (IV+dis)	FD CB XX C6	SET 4, A	CB E7
SET 0, A	CB C7	SET 4, B	CB E0
SET 0, B	CB C0	SET 4, C	CB E1
SET 0, C	CB C1	SET 4, D	CB E2
SET 0, D	CB C2	SET 4, E	CB E3
SET 0, E	CB C3	SET 4, H	CB E4
SET 0, H	CB C4	SET 4, L	CB E5
SET 0, L	CB C5	SET 5, (HL)	CB EE
SET 1, (HL)	CB CE	SET 5, (IX+dis)	DD CB XX EE
SET 1, (IX+dis)	DD CB XX CE	SET 5, (IV+dis)	FD CB XX EE
SET 1, (IV+dis)	FD CB XX CE	SET 5, A	CB EF
SET 1, A	CB CF	SET 5, B	CB E8
SET 1, B	CB C8	SET 5, C	CB E9
SET 1, C	CB C9	SET 5, D	CB EA
SET 1, D	CB CA	SET 5, E	CB EB
SET 1, E	CB CB	SET 5, H	CB EC
SET 1, H	CB CC	SET 5, L	CB ED
SET 1, L	CB CD	SET 6, (HL)	CB F6
SET 2, (HL)	CB D6	SET 6, (IX+dis)	DD CB XX F6
SET 2, (IX+dis)	DD CB XX D6	SET 6, (IV+dis)	FD CB XX F6
SET 2, (IV+dis)	FD CB XX D6	SET 6, A	CB F7
SET 2, A	CB D7	SET 6, B	CB F0
SET 2, B	CB D0	SET 6, C	CB F1
SET 2, C	CB D1	SET 6, D	CB F2
SET 2, D	CB D2	SET 6, E	CB F3
SET 2, E	CB D3	SET 6, H	CB F4
SET 2, H	CB D4	SET 6, L	CB F5
SET 2, L	CB D5	SET 7, (HL)	CB FE
SET 3, (HL)	CB DE	SET 7, (IX+dis)	DD CB XX FE
SET 3, (IX+dis)	DD CB XX DE	SET 7, (IV+dis)	FD CB XX FE
SET 3, (IV+dis)	FD CB XX DE	SET 7, A	CB FF
SET 3, A	CB DF	SET 7, B	CB F8
SET 3, B	CB D8	SET 7, C	CB F9
SET 3, C	CB D9	SET 7, D	CB FA
SET 3, D	CB DA	SET 7, E	CB FB
SET 3, E	CB DB	SET 7, H	CB FC
SET 3, H	CB DC	SET 7, L	CB FD

SLA (HL)	CB 26	SRL D	CB 3A
SLA (IX+dis)	DD CB XX 26	SRL E	CB 3B
SLA (IV+dis)	FD CB XX 26	SRL H	CB 3C
SLA A	CB 27	SRL L	CB 3D
SLA B	CB 20	SUB (HL)	96
SLA C	CB 21	SUB (IX+dis)	DD 96 XX
SLA D	CB 22	SUB (IV+dis)	FD 96 XX
SLA E	CB 23	SUB A	97
SLA H	CB 24	SUB B	90
SLA L	CB 25	SUB C	91
SRA (HL)	CB 2E	SUB D	92
SRA (IX+dis)	DD CB XX 2E	SUB E	93
SRA (IV+dis)	FD CB XX 2E	SUB H	94
SRA A	CB 2F	SUB L	95
SRA B	CB 28	SUB n	D6 XX
SRA C	CB 29	XOR (HL)	AE
SRA D	CB 2A	XOR (IX+dis)	DD AE XX
SRA E	CB 2B	XOR (IV+dis)	FD AE XX
SRA H	CB 2C	XOR A	AF
SRA L	CB 2D	XOR B	AB
SRL (HL)	CB 3E	XOR C	A9
SRL (IX+dis)	DD CB XX 3E	XOR D	AA
SRL (IV+dis)	FD CB XX 3E	XOR E	AB
SRL A	CB 3F	XOR H	AC
SRL B	CB 38	XOR L	AD
SRL C	CB 39	XOR n	EE XX

Opomba: Pri sprotnem indeksnem naslavljanju sledi kodu ukaza najprej odmik in nato število.