

9A	SBC A, D	C3 XX XX	JP naslov	CB 21	SLA C	CB 52	BIT 2, D
9B	SBC A, E	C4 XX XX	CALL NZ, naslov	CB 22	SLA D	CB 53	BIT 2, E
9C	SBC A, H	C5	PUSH BC	CB 23	SLA E	CB 54	BIT 2, H
9D	SBC A, L	C6 XX	ADD A, n	CB 24	SLA H	CB 55	BIT 2, L
9E	SBC A, (HL)	C7	RST 00	CB 25	SLA L	CB 56	BIT 2, (HL)
9F	SBC A, A	C8	RST Z	CB 26	SLA (HL)	CB 57	BIT 2, A
A0	AND A, B	C9	RET	CB 27	SLA A	CB 58	BIT 3, B
A1	AND A, C	CA XX XX	JP Z, naslov	CB 28	SRA B	CB 59	BIT 3, C
A2	AND A, D	CB 00	RLC B	CB 29	SRA C	CB 5A	BIT 3, D
A3	AND A, E	CB 01	RLC C	CB 2A	SRA D	CB 5B	BIT 3, E
A4	AND A, H	CB 02	RLC D	CB 2B	SRA E	CB 5C	BIT 3, H
A5	AND A, L	CB 03	RLC E	CB 2C	SRA H	CB 5D	BIT 3, L
A6	AND A, (HL)	CB 04	RLC H	CB 2D	SRA L	CB 5E	BIT 3, (HL)
A7	AND A, A	CB 05	RLC L	CB 2E	SRA (HL)	CB 5F	BIT 3, A
AB	XOR B	CB 06	RLC (HL)	CB 2F	SRA A	CB 60	BIT 4, B
A9	XOR C	CB 07	RLC A	CB 38	SRL B	CB 61	BIT 4, C
AA	XOR D	CB 08	RRC B	CB 39	SRL C	CB 62	BIT 4, D
AB	XOR E	CB 09	RRC C	CB 3A	SRL D	CB 63	BIT 4, E
AC	XOR H	CB 0A	RRC D	CB 3B	SRL E	CB 64	BIT 4, H
AD	XOR L	CB 0B	RRC E	CB 3C	SRL H	CB 65	BIT 4, L
AE	XOR (HL)	CB 0C	RRC H	CB 3D	SRL L	CB 66	BIT 4, (HL)
AF	XOR A	CB 0D	RRC L	CB 3E	SRL (HL)	CB 67	BIT 4, A
BO	OR B	CB 0E	RRC (HL)	CB 3F	SRL A	CB 68	BIT 5, B
B1	OR C	CB 0F	RRC A	CB 40	BIT 0, B	CB 69	BIT 5, C
B2	OR D	CB 10	RL B	CB 41	BIT 0, C	CB 6A	BIT 5, D
B3	OR E	CB 11	RL C	CB 42	BIT 0, D	CB 6B	BIT 5, E
B4	OR H	CB 12	RL D	CB 43	BIT 0, E	CB 6C	BIT 5, H
B5	OR L	CB 13	RL E	CB 44	BIT 0, H	CB 6D	BIT 5, L
B6	OR (HL)	CB 14	RL H	CB 45	BIT 0, L	CB 6E	BIT 5, (HL)
B7	OR A	CB 15	RL L	CB 46	BIT 0, (HL)	CB 6F	BIT 5, A
B8	CP B	CB 16	RL (HL)	CB 47	BIT 0, A	CB 70	BIT 6, B
B9	CP C	CB 17	RL A	CB 48	BIT 1, B	CB 71	BIT 6, C
BA	CP D	CB 18	RR B	CB 49	BIT 1, C	CB 72	BIT 6, D
BB	CP E	CB 19	RR C	CB 4A	BIT 1, D	CB 73	BIT 6, E
BC	CP H'	CB 1A	RR D	CB 4B	BIT 1, E	CB 74	BIT 6, H
BD	CP L	CB 1B	RR E	CB 4C	BIT 1, H	CB 75	BIT 6, L
BE	CP (HL)	CB 1C	RR H	CB 4D	BIT 1, L	CB 76	BIT 6, (HL)
BF	CP A	CB 1D	RR L	CB 4E	BIT 1, (HL)	CB 77	BIT 6, A
CO	RET NZ	CB 1E	RR (HL)	CB 4F	BIT 1, A	CB 78	BIT 7, B
C1	POP BC	CB 1F	RR A	CB 50	BIT 2, B	CB 79	BIT 7, C
C2 XX XX	JP NZ, naslov	CB 20	SLA B	CB 51	BIT 2, C	CB 7A	BIT 7, D