

PREDSTAVLJANJE 256 BIT-KOMBINACIJA

Gornje polje: Standardni znak

Donje polje: Kombinacija bušenja (Z = 12 vrstica, E = 11 vrstica)

Zonski deo (B-poz. 0-3)		Cifarski deo (Bit-pozicije 4 - 7)															
		0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F
		0000	0001	0010	0011	0100	0101	0110	0111	1000	1001	1010	1011	1100	1101	1110	1111
0	0000	Z09 81	Z91	Z92	Z93	Z94	Z95	Z96	Z97	Z98	Z98 1	Z98 2	Z98 3	Z98 4	Z98 5	Z98 6	Z98 7
1	0001	ZE9 81	E91	E92	E93	E94	E95	E96	E97	E98	E98 1	E98 2	E98 3	E98 4	E98 5	E98 6	E98 7
2	0010	E09 81	091	092	093	094	095	096	097	098	098 1	098 2	098 3	098 4	098 5	098 6	098 7
3	0011	ZE0 981	91	92	93	94	95	96	97	98	981	982	983	984	985	986	987
4	0100	Blank PRAZ NO	Z09 1	Z09 2	Z09 3	Z09 4	Z09 5	Z09 6	Z09 7	Z09 8	Z81	Z82	Z83	Z84	Z85	Z86	Z87
5	0101	Z	ZE9 1	ZE9 2	ZE9 3	ZE9 4	ZE9 5	ZE9 6	ZE9 7	ZE9 8	E81	E82	E83	E84	E85	E86	E87
6	0110	E	01	E09 2	E09 3	E09 4	E09 5	E09 6	E09 7	E09 8	081	ZE	083	084	085	086	087
7	0111	ZE0	ZE0 91	ZE0 92	ZE0 93	ZE0 94	ZE0 95	ZE0 96	ZE0 97	ZE0 98	81	82	83	84	85	86	87
8	1000	Z08 1	Z01	Z02	Z03	Z04	Z05	Z06	Z07	Z08	Z09	Z08 2	Z08 3	Z08 4	Z08 5	Z08 6	Z08 7
9	1001	ZE8 1	ZE1	ZE2	ZE3	ZE4	ZE5	ZE6	ZE7	ZE8	ZE9	ZE8 2	ZE8 3	ZE8 4	ZE8 5	ZE8 6	ZE8 7
A	1010	E08 1	E01	E02	E03	E04	E05	E06	E07	E08	E09	E08 2	E08 3	E08 4	E08 5	E08 6	E08 7
B	1011	ZE0 81	ZE0 1	ZE0 2	ZE0 3	ZE0 4	ZE0 5	ZE0 6	ZE0 7	ZE0 8	ZE0 9	ZE0 82	ZE0 83	ZE0 84	ZE0 85	ZE0 86	ZE0 87
C	1100	Z0	Z1	Z2	Z3	Z4	Z5	Z6	Z7	Z8	Z9	Z09 82	Z09 83	Z09 84	Z09 85	Z09 86	Z09 87
D	1101	E0	E1	E2	E3	E4	E5	E6	E7	E8	E9	ZE9 82	ZE9 83	ZE9 84	ZE9 85	ZE9 86	ZE9 87
E	1110	Blank BUS 082	E091	02	03	04	05	06	07	08	09	E09 82	E09 83	E09 84	E09 85	E09 86	E09 87
F	1111	0	1	2	3	4	5	6	7	8	9	ZE0 982	ZE0 983	ZE0 984	ZE0 985	ZE0 986	ZE0 987