

THE DRIVER HAS BEEN PATCHED TO WORK WITH DATAPRODUCTS LINE PRINTER

```
>RUN $ZAP
ZAP>LTDRV.TSK/AB
_3:303D
003:000303D 377          ;FOR FUJI CENTRONICS
_374                    ;FOR DATAPRODUCTS
_X
```

SECOND PATCH FOR LOWER-UPPER CASE (DATAPRODUCTS)

```
>RUN $ZAP
ZAP>LTDRV.TSK/AB
_4:440/140100
_140100U
_140000
_X
```

AFTER THE PATCH, THE DRIVER SHOULD BE RELOADED IN VMR

```
>ASN TV!:=SY!
>ASN TV!:=LB!
>PIP SYSTEM.SYS/NU/CO/BL:498.=-SYSTEM.TSK
>VMR $SYSTEMVMR
_00 SYSTEM
XDT>G
>TIM DD-MMM-GG HH:MM
>SAV /WB
```

THE CABLE PINOUT IS AS FOLLOWS:

SIGNAL NAME	CENTRONICS	DATAPRODUCTS
STROBE	1	J
DATA 1	2	B
DATA 2	3	F
DATA 3	4	L
DATA 4	5	R
DATA 5	6	U
DATA 6	7	Z
DATA 7	8	N
DATA 8	9	P
BUSY	11	E
PAPER EMPTY	12	EE
FAULT	32	Y
GROUND	19-30	AA

THE PAPER EMPTY DOES NOT EXIST ON THE DATAPRODUCTS PRINTER SO IT IS GROUNDED.