

RSX-11M V3.2
UTILITIES
BRU

Seq 5.1.17.12 M

1 of 2 URB

BRU TAPE LABEL PADDED WITH NULLS (SPR 11-30794 LK)

PROBLEM
STATEMENT

BRU didn't pad the tape label correctly in the ANSI VOL1 record when the tape label had less than 6 characters. This caused problems when BRU did a verify or compare operation or when we made an attempt to mount or dismount the tape.

RESPONSE

The following is a cumulative patch with .IDENT /01.2/ correcting the parsing algorithm.

Create the file [74,40]BRUPAR.PAT:

```

        .TITLE BRUPAR
;
; COPYRIGHT (C) 1980
; DIGITAL EQUIPMENT CORPORATION, MAYNARD, MASS.
;
; MODIFICATIONS
;
; 01.1 - SET PROPER BIT FOR /WINDOWS QUALIFIER
; 01.2 - PUT BLANKS INTO THE LABEL FIELD
        .IDENT /01.1/
        .PSECT
.BLK.=.
SETQ1=.BLK.+5470
.=.BLK.+760
        .WORD SETQ1 ; SET KEYWORD BIT IN THIS WORD
.=.BLK.

```