

RSX-11M V3.2
UTILITIES
BRU

Seq 5.1.17.13 M

1 of 5

/TAPELABEL DOESN'T WORK DURING RESTORE (SPR 11-32313 LK)

**PROBLEM
STATEMENT**

The /TAPELABEL switch does not work during the restore operation from a tape.

RESPONSE

BRU
does not check the input volume name during the restore operation from a tape. The following cumulative patch will correct this problem.

Create the file TAPEIO.PAT:

.TITLE TAPEIO

; COPYRIGHT (C) 1980
; DIGITAL EQUIPMENT CORP., MAYNARD, MASS.

; MODIFICATIONS:

; 01.1 --

; CORRECT ERROR MSG IF TAPE DRIVER NOT LOADED

; WAIT FOR DEVICE DETACHES TO AVOID EXIT WITH OUTSTANDING I/O

; MAKE TAPEIO SERIALLY REUSABLE

; CORRECT ERROR RETURN AT BOT FOR RESTOPE

; CORRECT "MOUNT TAPE" MESSAGE

; CORRECT TAPE FORMAT IF NO FILES FOUND

; 01.2 --

; INPUT TAPE LABEL VERIFICATION