

K201 - Quiz 6

1. You are given a set of cards with the following card layout:

<u>Columns</u>	<u>Variable</u>	<u>Form</u>
1-9	IDS	
12-17	NUM	
22-25	PTI	XX _A XX
26-33	QTI	XXXXXX _A XX
34-35	Y	XX _A

Cards are sorted according to control variable NUM. The end-of-data card has a negative number in the field IDS. Prepare a complete FORTRAN program to read these cards and copy them on magnetic tape with no space between the fields on the tape. Be sure to terminate this program properly.

1	5	6	7	10	15	20	25	30	35	40	45	50	55	60
10	READ(5,1)IDS,NUM,PTI,QTI,Y													
1	FORMAT(I9,2X,I6,4X,F4.2,F8.2,F2.0)													
	IF(IDS.LT.0)GOT100													
	WRITE(11,2)IDS,NUM,PTI,QTI,Y													
2	FORMAT(I9,I6,F4.2,F8.2,F2.0)													
	GOT10													
100	ENDFILE 11													
	REWIND 11													
	STOP													
	END													